

SLI-32310R-GAR

Starter Battery for Lawn Mowers and Power Equipment
Base hold-down: BX · Polarity layout: A(- , +) · Terminal type: FD

Capacity (20h rate)	32 Ah
Cold Cranking Current (EN)	310 A @ -18°C
Cold Cranking Current (SAE)	330 A @ -18°C
Reserve Capacity (RC)	50 min
Weight (with acid)	7.8 kg

About SKANBATT SLI – Garden & Power Equipment

SKANBATT SLI Garden batteries are designed for reliable starting and stable electrical performance in lawn mowers, garden tractors and other small engine equipment. Produced by one of the world's leading manufacturers of starter batteries, the SLI range is built according to OEM principles to ensure documented performance and consistent quality over time.

For seasonal equipment, correct charging and storage are essential. Keeping the battery fully charged during off-season helps preserve capacity and ensures dependable start power when the season begins.

Technical Specifications

Dimensions (L × W × H)	197 × 129 × 185 mm
Base hold-down	BX
Polarity layout	A(- , +)
Terminal type	FD
Nominal voltage	12 V
Technology	Lead-Acid (SLI)
Capacity (20h)	32 Ah
Reserve capacity (RC)	50 min
Cold cranking (EN, -18°C)	310 A
Cold cranking (SAE, -18°C)	330 A
Handle	Yes
Lid type	Flat/Sealed Type
Weight (with acid)	7.8 kg

Charging, Maintenance & Storage

- Recommended charging voltage: 14.4 V at 25°C.
- Float / maintenance voltage: 13.5–13.8 V at 25°C.
- Temperature compensation of charging voltage is recommended (approx. $-24 \text{ mV/}^{\circ}\text{C}$ for 12V batteries).
- Recharge promptly after deep discharge to reduce risk of sulfation.
- Avoid prolonged overcharging as it may reduce service life.
- For storage: keep the battery fully charged and recharge every 3–6 months depending on ambient temperature.
- Higher temperatures increase self-discharge rate.
- Disconnect from vehicle/equipment during extended storage to prevent parasitic drain.

SKANBATT – Battery Solutions Made Easy

Specifications are typical values and may vary depending on production tolerances and operating conditions.