

BYH Series Non-polarity DC Isolator Switches

4P 1000V 32A



- 1 Waterproof Plug
- 2 IP66 Ingress Protection
- 3 Sealed Plug
- 4 OFF
- 5 LOCK
- 6 Standard
- 7 Brand
- 8 Type
- 9 ON
- 10 Knob

BYH-32

BYH-32 with MC4



Accessories

Application

ZBENY BYH-32 true DC isolator switch in IP66 enclosure is developed for solar residential and commercial PV rooftop systems, should be installed between solar panels and inverter for DC power isolation. The first DC isolator complies with DC-PV2 AS60947.3 2018 standard. The patent arcextinguish chamber and qualify material ensure the DC isolator's reliable and long working life. Breather valve is attached on the enclosure bottom. Max voltage up to 1000V.

Feature

- IP66,UV Resistance
- Arcing Time < 3ms
- Earth Terminal
- IEC60947-3, AS60947.3
- 2 Poles, 4 Poles Available(Single | Double String)
- DC-PV2 / DC-21B: 32A up to 1000VDC

Appearance Introduction



Parameter

Electrical Characteri	stics				
Туре		BYH-32, BYH-32M1, BYH-32M2			
Function		Isolator, Control			
Standard		IEC60947-3, AS60947.3			
Utilization category		DC-PV2 / DC-21B			
Pole		4P			
Rated frequency		DC			
Rated operational volt	age (U _e)	500V, 600V, 800V, 1000V			
Rated operational cur	rent (I_e)	See the next page			
Rated insulation voltage	ge (<i>U</i> ,)	1200V			
Conventional free air t	hermal current(I _{th})	Ш			
Conventional enclose	d thermal current(I _{the})	Same as I_{e}			
Rated short-time with	stand current (I _{cw})	1kA,1s (4,4B); 1.7kA, 1s (2H)			
Rated short-time making	ing capacity (<i>I_{cm}</i>)	1.7kA(4,4B); 3kA(2H)			
Rated conditional sho	rt-circuit current (I _{cn})	3kA			
Rated impulsed withst	tand voltage (U_{imp})	8.0kV			
Overvoltage category		II			
Suitability for isolation		Yes			
Polarity		No polarity, "+" and "-" polarities could be interchanged.			
Service Life/Cycle O	peration				
Mechanical		15000			
Electrical		1000			
Installation Environr	nent				
Ingress Protection	Enclsoure	IP66			
Ingress Frotection	Switch body	IP20			
Storage Temperature		-50°C ~ +90°C			
Operation Temperature		-40°C ~ +85°C			
Mounting Type		Vertically or horizontally			
Pollution degree		3			
Suitable environment		Outdoor / Indoor			

Z/BENY

BYH Series Non-polarity DC Isolator Switches

Breathing Valve



Remarks: ZJBENY DC Isolator has a breathing valve already, to avoid the condensation issue.

Identification		Rating data			
Switch, unenclosed - catalogue number (with DC-PV2 rating)		BYH.1-32, BYH.2-32			
Specific dedicated individual enclosure - catalogue number (with minimum IP56NW rating)		BYH-32 IP66NW			
Assembly of switch and spe individual enclosure - catalo		1			
Ith rated thermal current, une shade ambient air temperation			32 amps		
Ime rated thermal current, indoors, at 40°C shade ambient air temperature, in a specific dedicated enclosure		32 amps			
<i>Ime</i> rated thermal current <u>outdoors</u> at 40°C shade ambient air temperature <u>without solar effects in</u> a specific dedicated enclosure rated IP66NW		32 amps			
<i>Ime</i> solar current value outdoors at 60°C shade ambient air temperature (see D.8.3.11,table D3), with solar effects in a specific dedicated enclosure rated IP66NW		29 amps			
		U _e rated operational voltage DC Volts	<i>l</i> _e ; DC-PV2 rated operational current Amps	I _(make) and I _{c(break)} DC-PV2 4 x I _e Amps	
		300	32	128	
4-pole		500	32	128	
2 pole in series	(_1/_2/)	600	13	52	
4		800	9	36	
		1000	9	36	
2-pole 4 pole in series		300	32	128	
	(_1/_2/_3/_4/)	500	32	128	
		600	32	128	
4B		800	32	128	
		1000	32	128	



Wiring Diagram for Rated operational voltage Ue (V) & Rated operational current le (A)

Contacts wiring diagram	300V	500V	600V	800V	1000V	Poles in series	Number of Strings	Type Number
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	32A	32A	13A	9A	9A	2	2	4
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	40A	40A	1	1	1	4	1	2H
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	32A	32A	32A	32A	32A	4	1	4B
	32A	32A	32A	32A	32A	4	1	4S

Switching Configurations

Туре	4-pole	2-pole 4 Paralleled Poles	4-pole with Input and Output bottom	4-pole with Input on top Output bottom
/	4	2H	4B	4S
Contacts Wiring graph	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	$\begin{array}{cccccccccccccccccccccccccccccccccccc$
Switching example				

Bridging links installation

Installed incorrectly





Installed correctly

* Warning: Verify that all connections (including bridging link connections) are suitable for the rated current, prepared to ensure only conductive parts are clamped and tightened to the manufacturers required torque before energization.

Z/BENY

BYH Series Non-polarity DC Isolator Switches

Terminals / connection

Туре		BYH-32, BYH-32M1, BYH-32M2		
Number of poles		4-pole		
Terminal designation, main circuit		1; 3; 5; 2; 4; 6; 7; 8		
Type of terminal, main circuit		Screw terminal		
Rated cross section area, main circuit		4.0-16mm ²		
Type of onductor		4-16mm ² (Rigid: Solid or Stranded)		
Type of onductor	222	4-10mm ² (Flexible)		
Number of conductors per terminal		1		
Required preparation of the conductor		Yes		
Stripping length (mm), main circuit		8mm		
Tightening torque (M4), main circuit		Min: 1.2Nm		
		Max: 1.8Nm		

IP Rating



Remarks:

ZJBENY DC Isolator can be installed in any direction, but must do well performance for waterproof.

Dimensions(mm)









Data according to AS60947-3:2018

Main Contacts		Туре	BYH-32	Appendix B5
Rated thermal current I _{the}		А	32	Making &
Rated insulation voltage U _i		V	1000	Breaking
Distance of contacts (per pole)		mm	8	5x
Rated operational current le (DC-PV2)				operations
1 pole	300V	А	25	100
I	400V	А	10	40
_1/	500V	А	8	32
	600V	А	8	32
	800V	А	3	12
	1000V	А	2	8
I-pole	500V	А	32	128
2 pole in series	600V	А	13	52
	700V	А	9	36
_1/_2/	800V	А	9	36
	900V	А	9	36
	1000V	А	9	36
2-pole	500V	А	40	160
parallel poles H	600V	А	1	/
	700V	А	1	/
$\begin{array}{c} 1 \\ 2 \\ 3 \\ 4 \\ \end{array}$	800V	А	/	1
	900V	А	/	1
	1000V	А	/	1
-pole	500V	А	32	128
pole in series B	600V	А	32	128
	700V	А	32	128
_1/_2/_3/_4/	800V	А	32	128
	900V	А	32	128
	1000V	А	32	128